

Powerful and compact, the GoodWe ET50 hybrid inverter is ideal for Commercial and Industrial (C&I) energy storage solutions. The inverter is compatible with a range of battery capacities, and leverages intelligent operating modes to optimize system performance across various scenarios such as self-consumption, peak shaving, time-of-use and grid support. Its parallel connection capability facilitates seamless expansion for both on-grid and off-grid setups. When coupled with the Static Transfer Switch (STS) Box, the system supports dependable UPS-level switching to backup mode. Paired with the GoodWe Lynx C battery system, GoodWe provides a complete energy storage solution.



Parallel connection



Peak shaving and grid support



Powerful back-up with STS box





Technical Data	GW40K-ET-10	GW50K-ET-10	
Battery Input Data			
Battery Type	li	-lon	
Nominal Battery Voltage (V)		500	
Battery Voltage Range (V)	200 ~ 800		
Start-up Voltage (V)	2	200	
Number of Battery Input		1	
Max. Continuous Charging Current (A)	100		
Max. Continuous Discharging Current (A)		00	
Max. Charging Power (W)	44000	55000	
Max. Discharging Power (W)	44000	55000	
PV String Input Data			
Max. Input Power (W)	60000	75000	
Max. Input Voltage (V)		000	
MPPT Operating Voltage Range (V)		~ 850	
Start-up Voltage (V)		200 620	
Nominal Input Voltage (V)			
Max. Input Current per MPPT (A) Max. Short Circuit Current per MPPT (A)	42 / 32 / 42 55 / 42 / 55	42 / 32 / 42 / 32 55 / 42 / 55 / 42	
Number of MPP Trackers	3		
Number of Strings per MPPT	2		
AC Output Data (On-grid)			
Nominal Output Power (W)	40000	50000	
Nominal Output Power (W) Nominal Apparent Power Output to Utility Grid (VA)	4000 4000	50000 50000	
Max. Apparent Power Output to Utility Grid (VA)	40000	50000	
Max. Apparent Power Gulput to Glilly Grid (VA)	40000	50000	
Nominal Output Voltage (V)		3L / N / PE	
Output Voltage Range (V)*2	176 ~ 276		
Nominal AC Grid Frequency (Hz)	50 / 60		
AC Grid Frequency Range (Hz)		~ 65	
Max. AC Current Output to Utility Grid (A)	60.6	75.8	
Max. AC Current From Utility Grid (A)	60.6 75.8		
Power Factor Max. Total Harmonic Distortion	~1 (Adjustable from 0.8 leading to 0.8 lagging) <3%		
		3 /6	
AC Output Data (Back-up) 1			
Back-up Nominal Apparent Power (VA)	40000	50000	
Max. Output Apparent Power (VA)	44000 (48000 @ 60sec, 60000 @ 10sec) 55000 (60000 @ 60sec, 75000 @ 10sec)		
Max. Output Current (A) Nominal Output Voltage (V)	66.7 83.3 380 / 400, 3L / N / PE		
Nominal Output Vollage (V) Nominal Output Frequency (Hz)		/60	
Output THDv (@Linear Load)		3%	
Efficiency			
•		100	
Max. Efficiency	98.1% 97.5%		
European Efficiency Max. Battery to AC Efficiency	97.5% 97.7%		
MPPT Efficiency	99.0%		
		078	
Protection			
Residual Current Monitoring	Integrated		
PV Reverse Polarity Protection	Integrated		
Battery Reverse Polarity Protection	Integrated		
Anti-islanding Protection AC Overcurrent Protection	Integrated Integrated		
AC Overcurrent Protection AC Short Circuit Protection		Integrated	
AC Overvoltage Protection	Integrated		
DC Switch	Integrated		
DC Surge Protection	Type II (Type I + II Optional)		
AC Surge Protection	Type II		
AFCI	Optional		
Remote Shutdown	Integrated		
General Data			
Operating Temperature Range (°C)	-35	~ +60	
Relative Humidity		0 ~ 95%	
Max. Operating Altitude (m)	4000		
Cooling Method	Smart Fan Cooling		
User Interface	LED, WLAN + APP		
	CAN		
Communication with BMS		105	
Communication with BMS Communication with Meter	RS	6485	
Communication with BMS Communication with Meter Communication with Portal	RS LAN / 4G	(Optional)	
Communication with BMS Communication with Meter Communication with Portal Weight (kg)	RS LAN / 4G 62	(Optional) 65	
Communication with BMS Communication with Meter Communication with Portal Weight (kg) Dimension (W x H x D mm)	RS LAN / 4G 62 520 × 6	(Optional) 65 60 × 260	
Communication with BMS Communication with Meter Communication with Portal Weight (kg) Dimension (W x H x D mm) Topology	RS LAN / 4G 62 520 × 6 Non-i	(Optional) 65 60 × 260 solated	
Communication with BMS Communication with Meter Communication with Portal Weight (kg) Dimension (W x H x D mm)	RS LAN / 4G 62 520 × 6 Non-i	(Optional) 65 60 × 260	

^{*1:} Backup function can be only realized with STS Box (Static Transfer Switch).
*2: Output Voltage Range: phase voltage.
*: Please visit GoodWe website for the latest certificates.